

KVV-65A-3XKIT



Tri-sector solution that includes 3 KVV-65A-R2 antennas and mounting kit to install them on a pipe

- Suitable for attachment to 3.5-6.6 in or 89-168 mm outer diameter pipe
- Compatible with canister concealment shrouds with inner diameter > 23.5 in (597mm)
- Minimum shroud diameter is the same for all applicable pipe diameters

General Specifications

Band	Multiband
Performance Note	Outdoor usage
RF Connector Interface	4.3-10 Female
RF Connector Location	Bottom
RF Connector Quantity, mid band	12
RF Connector Quantity, low band	6
RF Connector Quantity, total	18

Electrical Specifications

Operating Frequency Band	1695 – 2690 MHz 617 – 960 MHz
---------------------------------	---------------------------------

Packaging and Weights

Width, packed	601 mm 23.661 in
Depth, packed	1027 mm 40.433 in
Length, packed	1667 mm 65.63 in
Weight, gross	128.8 kg 283.955 lb

* Footnotes

Performance Note	Severe environmental conditions may degrade optimum performance
-------------------------	---